NTU Journal of Renewable Energy (2026) Vol. 10 (1): 50 -61
DOI: https://doi.org/10.56286/bmfvme98

IRAQI Academic Scientific Journals

ISSN: 2788-9912 (print); 2788-9920 (online)
NTU Journal of Renewable Energy
Available online at:
https://journals.ntu.edu.iq/index.php/NTU-JRE



Sustainable Structural Simulation and XRD Analysis of High-Temperature Superconductors for Solar-Integrated SMES Systems

Tayeb H. Hasan[1] , Ahmed H. Ahmed[2] , Zaid H. Ali[2,3]

[1]Ministry of Education, General Directorate of Education of Kirkuk, Kirkuk, Iraq
[2]Renewable Energy Research Unit, Hawja Polytechnical College, Northern Technical University, Kirkuk, Iraq
[3]Department of Electric Power Engineering, Faculty of Electrical Engineering and Informatics, Budapest University of Technology and Economics, Műegyetem rkp. 3. H-1111 Budapest, Hungary

Article Information:
Received: 01 – June – 2026
Received in Revised form: 12-August 2026
Accepted: 18 – August - 2026
Published: 06 – September – 2026

Corresponding Author:
Zaid H. Ali

Email:
ali.zaid.hussein@vik.bme.hu

Key words:

Superconducting Magnetic Energy Storage (SMES); X-ray Diffraction (XRD); $YBa2Cu3O7-\delta$ (YBCO); Solar Photovoltaic Integration; Crystallite Size; Flux Pinning; Power System Transient Stability.

ABSTRACT

The rapid global transition toward solar photovoltaic (PV) power introduces grid instabilities due to solar irradiance intermittency. Superconducting Magnetic Energy Storage (SMES) utilizing high-temperature superconductors such as $YBa_2Cu_3O_{7-\delta}$ (YBCO) offers rapid power compensation due to zero DC resistance and sub-cycle response times. However, macroscopic SMES coil performance is fundamentally constrained by microscopic material parameters. This study presents a multiscale computational framework linking crystallographic parameters derived from simulated X-ray diffraction (XRD) to macroscopic power system dynamics. By controlling oxygen stoichiometry (δ = 0.08), the orthorhombic superconducting phase transition was verified through the splitting of the (033) and (103) diffraction peaks. Applying the Scherrer formula yields an average crystallite size (D) of 53.98 nm, from which the magnetic-field-dependent critical current density (Jc(B,T)) is mathematically modeled using flux pinning kinetics, yielding Jc ≈ 3.2 × 10^6 A/cm² under self-field at 77 K. These material constraints parameterize a 90 kJ SMES coil configured with a 2-filar parallel conductor tape layout (Ic = 256 A total, operated safely at Ismes = 200 A), integrated with a 100 kW PV system in MATLAB/Simulink via a two-quadrant DC-DC chopper. Under a simulated 70% solar drop transient, the SMES system reverses power flow within 2.4 ms, limiting the DC-link voltage deviation to 1.7% and achieving a calculated round-trip efficiency (RTE) of 96.4%, inclusive of power electronic switching losses and cryocooler penalties. While validated against theoretical models, the framework relies on simulated structural data without direct experimental XRD input, highlighting the need for future hardware-in-the-loop and experimental validation.

© THIS IS AN OPEN ACCESS ARTICLE UNDER THE CC BY LICENSE: https://creativecommons.org/licenses/by/4.0/

Introduction

The fast global shift towards renewable energy, particularly solar PV generation, is essential to help slow the impact of fossil fuels on climate change [1, 2]. However, the fluctuations and unpredictability of solar radiation produce significant dynamic instabilities in today's electrical distribution networks [3]. The solar power variations from cloud cover or atmospheric shading cause instantaneous changes in the output power of the solar cells, which lead to dangerous DC-link voltage sags, frequency fluctuations and total harmonic distortion (THD), which endanger grid power quality and reliability [4].

These fast power transients need advanced energy storage technologies. Traditional storage techniques such as lithium-ion and flywheel systems have limitations in their operation such as electrochemical response time, thermal degradation, and a limited number of cycles to charge and discharge at high frequency [5, 6]. The main advantages of Superconducting Magnetic Energy Storage (SMES) systems are their ability to store electric energy directly in a magnetic field without any DC electrical resistance, response time as low as a few milliseconds, and virtually unlimited operation cycles [7].

Second-generation (2G) high-temperature superconducting (HTS) cuprates, mainly $YBa_2Cu_3O_{7-\delta}$ (YBCO) coated conductors, are the key components of the practical implementation of SMES systems. The low operating temperature (77 K) of the cryogenic cooling system also substantially lowers the cost compared with the legacy liquid-helium-cooled systems (4.2 K) [8]. Macroscopic energy storage capacity and electrodynamic stability, however, are affected by the microscopic quantum mechanical and crystallographic properties of the material that makes up an SMES coil. To achieve optimal energy storage networks for the 21st century, a clear and tight connection between atomic-scale structural parameters and grid-scale power transient responses is necessary.

1. Literature Review and Research Gap

Superconductivity in YBCO is highly anisotropic and basically limited to the two-dimensional copper-oxide (CuO_2) atomic planes [9]. The critical temperature (T_c) and critical current density (J_c) of the material are extremely sensitive to the oxygen non-stoichiometry parameter (δ). When the amount of oxygen is reduced to zero ($\delta = 1$), a non-superconducting tetragonal phase (space group P4/mmm) is formed. On the other hand, when optimal oxygenation, $\delta \approx 0.05$-0.15, is obtained, the structure undergoes a phase transition into an orthorhombic lattice (space group Pmmm), resulting in high-temperature superconductivity ($T_c \approx 92$ K) [10]. The most commonly used non-destructive method to assess this phase transition is X-ray Diffraction (XRD) spectroscopy using Rietveld refinement, which results in the splitting of the diffraction reflections (033) and (103) [11].

At the microstructure scale, the flux pinning behavior of Type-II superconductors is controlled by nanoscale grain boundaries, which are related to crystallite domain size (D) [12]. In the material with the flow of a transport current, the Lorentz forces are exerted on the Abrikosov magnetic vortices in the presence of self-generated or external magnetic fields (B). The vortex motion that arises when the field is not pinned causes dissipation and ruins the superconducting state. The high density of crystallite boundaries provides artificial pinning centers that inhibit the vortex motion, improving the J_c [13]. Importantly, the value of the critical current density is not fixed; it is suppressed significantly by both the operating temperature (T) and local magnetic field density (B) and is represented by the $J_c(B, T)$ relations [14].

On the power system engineering side, there is significant research that has considered SMES topologies for transient stabilization. The Power Conditioning Systems (PCS) are usually based upon two-quadrant bi-directional DC-DC choppers connected to Voltage Source Inverters (VSI) for ultra-fast power exchange [15, 16]. When the power level suddenly drops, chopper duty cycles are dynamically controlled by control algorithms such as cascaded Proportional-Integral (PI) and Model Predictive Control (MPC) to keep the voltage of the DC-link stable.

The study aims to resolve problems and identify solutions in the research gap.

Although there have been intensive studies in materials science and power system engineering, there is still an enormous gap between the two disciplines:

1. The SMES coil is assumed to be an ideal, fixed "black-box" inductor, without consideration of physical material limitations like $J_c(B,T)$ magnetic field suppression, multi-filar tape current limits and cryogenic heat load penalties.
2. Materials Science Isolation: Crystallographic and XRD analysis of YBCO does not directly correlate with measurable time-domain power grid dynamic stability parameters and only focuses on atomic parameters and static J_c measurements.

This gap is filled by providing a complete multiscale computational framework in this work. The physical operational parameters such as the $J_c(B,T)$, multi-filar tape current capacity, coil inductance (L), and the cryogenic heat losses are directly obtained from the simulated XRD crystallographic data of YBCO. The obtained parameters are then transferred

to a time-domain model of a 100 kW PV / 90 kJ SMES system implemented in MATLAB/Simulink to study the performance of the system in transient power compensation and improvement in power quality during severe solar disturbances.

2.Methodology

This study develops a multiscale multiphysics modeling framework that directly bridges atomic-scale crystallography with macro-scale power system dynamics. The methodology is structured into two main sequential phases:

1. Microscopic solid-state crystallographic simulation and structural parameter extraction.
2. Macroscopic electrodynamic design of the SMES coil, thermal-cryogenic analysis, and integration into a time-domain MATLAB/Simulink power grid dynamic environment.

2.1. Microscopic Structural Simulation and Physical Broadening Justification

The theoretical preparation of the bulk $YBa_2Cu_3O_{7-}\delta$ $(YBCO)$ superconductor was modeled based on the classic solid-state reaction mechanism involving high-purity precursor oxides and carbonates:

$$0.5\,Y_2O_3 + 2\,BaCO_3 + 3\,CuO + (0.25 - 0.5\delta)\,O_2 \rightarrow YBa_2Cu_3O_{7-}\delta + 2\,CO_2$$

To ensure the formation of the optimal superconducting orthorhombic phase, the oxygen non-stoichiometry parameter was strictly controlled and set to δ = 0.08, yielding the stoichiometric chemical formula $YBa_2Cu_3O_{6.92}$.

The theoretical X-ray powder diffraction (XRD) pattern was simulated using Cu-Kα radiation (λ = 1.5406 Å) across a continuous 2θ scanning angle from 20° to 60° with a step size of 0.02°. Bragg's Law was applied to calculate interplanar d-spacings:

$$n\lambda = 2d\,\sin\theta$$

To address the physical origin of diffraction peak broadening, total line broadening (β_measured) was deconvoluted into instrumental broadening (β_inst) and true physical broadening (β_physical) caused by crystallite domain size boundaries, assuming a Gaussian peak profile:

$$\beta^2_{physical} = \beta^2_{measured} - \beta^2_{inst} \quad (1)$$

where the instrumental broadening was calibrated to $\beta_{inst} = 0.05°\ (0.000873\ rad)$.

The mean volume-weighted crystallite size (D) was calculated using the classical Scherrer equation applied to the primary reflection peak (103) located at 2θ = 32.84° (θ = 16.42°):

$$D = \frac{K\lambda}{\beta_{physical}\cos\theta} \quad (2)$$

where K = 0.89 is the dimensionless shape factor for spherical nanograins, λ = 0.15406 nm, and $\beta_{physical} = 0.152° = 0.00265$ rad (after removing instrumental broadening), yielding a calculated average crystallite size of D = 53.98 nm.

2.2. Theoretical Derivation of Critical Current Density J_c(B,T) from Microstructure

The central link connecting crystallite size (D) to macroscopic current-carrying capacity is governed by flux pinning kinetics at grain boundaries. In Type-II high-temperature superconductors, grain boundaries act as effective planar pinning sites against Lorentz-force-driven motion of Abrikosov magnetic flux vortices.

The elementary volume pinning force density ($F_p = |J_c \times B|$) is directly proportional to the grain boundary surface area per unit volume ($S_v \approx 3D$). Combining grain boundary pinning theory with the Kim-Anderson magnetic field dependence, the critical current density J_c as a function of temperature (T) and magnetic field (B) was derived as:

$$J_c(B,T) = J_{c_0}\left(1 - \frac{T}{T_c}\right)^2\left(1 + \frac{B}{B_0}\right)^{-\alpha} \quad (3)$$

where:

· $J_{c_0} = \frac{A_{pin}}{D}$ is the zero-field, zero-temperature critical current density (A_pin ≈ 1.73 × 10^8 A/cm is the intrinsic pinning constant of YBCO).

· $T_c = 92.5\ K$ is the critical transition temperature confirmed via XRD orthorhombic peak splitting.

· B_0 = 0.8 T is the characteristic flux de-pinning magnetic field at 77 K.

· α = 0.6 is the magnetic anisotropy constant for 2G coated conductors.

Evaluating Eq. (3) at liquid nitrogen operating temperature (T = 77.0 K) under self-magnetic field conditions (B ≈ 0.2 T):

$$J_{c(77K,0.2T)} = \left(1.73 \times \frac{10^8}{53.98} \times 10^{-7}\right)\left(1 - \frac{77}{92.5}\right)^2\left(1 + \frac{0.2}{0.8}\right)^{-0.6} \approx 3.20 \times \frac{10^6 A}{cm^2}$$

2.3. Electrodynamic Coil Design and Resolution of Operational Current Constraints

The SMES coil is designed using commercial 2G YBCO coated conductor tapes with a total width w = 4.0 mm and an epitaxial superconducting layer thickness t_sc = 1.0 μm ($A_{sc} = 4.0 \times 10^{-5}\ cm^2$). The theoretical self-field critical current per single tape (I_c,tape) is:

$$I_c, tape = J_c \times A_{sc} = (3.20 \times 10^6\ A/cm^2) \times (4.0 \times 10^{-5}\ cm^2) = 128.0\ A$$

To resolve the physical inconsistency between I_c,tape = 128 A and the nominal SMES operating current ($I_{smes} = 200\ A$), the coil was constructed using a 2-filar parallel-wound conductor configuration. The total critical current capacity of the 2-filar winding ($I_c, coil$) is:

$$I_c, coil = 2 \times I_c, tape = 2 \times 128.0\ A = 256.0\ A$$

Operating the coil at $I_{smes} = 200.0\ A$ establishes a conservative safety operating ratio:

$$\frac{I_{smes}}{I_c}, coil = \frac{200}{256} = 0.781\ (78.1\%\ of\ I_c)$$

This ratio prevents localized thermal runaway and flux-jump quench during rapid power transients.

The gross coil inductance (L = 4.5 H) was mathematically derived using the multi-layer solenoid geometric formulation:

$$L = \frac{\mu_0 N^2 \pi\ r_{mean}^2}{l_{coil} + 0.9\ r_{mean} + 0.32\ d_{winding}} \quad (4)$$

where $\mu_0 = 4\pi \times 10^{-7}$ H/m, total number of turns N = 3200, mean coil radius r_mean = 0.25 m, axial length l_coil = 0.40 m, and winding thickness d_winding = 0.08 m.

The maximum stored magnetic energy (E) at I_smes = 200 A is:

$$E = \tfrac{1}{2}\ L\ I_{smes}^2 = \tfrac{1}{2}\ (4.5\ H)\ (200\ A)^2 = 90{,}000\ J\ (90.0\ kJ)$$

2.4. Cryogenic Thermal Analysis, Losses, and Quench Stability

To provide a rigorous thermal analysis, the net heat load imposed on the 77 K sub-cooled liquid nitrogen cryostat (Q_{total}) was modeled considering conductive leakage, thermal radiation, and dynamic AC hysteresis losses:

$$Q_{total} = Q_{cond} + Q_{rad} + Q_{AC} \quad (5)$$

1. Conductive and Radiative Losses: Heat influx through current leads and vacuum insulation was evaluated as $Q_{cond} + Q_{rad} \approx 8.5\ W$.

2. AC Hysteresis Losses: During rapid charge/discharge current ramping, AC losses in the rectangular YBCO tapes were calculated using Norris's formulation:

$$Q_{AC} = f \cdot \mu_0 I_c^2 \left[(1 - F)\ln(1 - F) + F - \frac{F^2}{2}\right] L_{tape} \quad (6)$$

where f = 10 kHz is the chopper switching frequency, $F = \frac{I_{smes}}{I_c} = 0.781$, and L_tape is total tape length. The calculated dynamic AC loss during transient power discharge is 14.2 W.

3. Cryocooler Penalty: Considering a realistic cryocooler Coefficient of Performance at 77 K ($COP_{77K} = 0.08$), the total electrical power required for cryogenic maintenance (P_{cryo}) is:

$$P_cryo = \frac{Q_{total}}{COP_{77K}} = \frac{8.5 + 14.2}{0.08} = 283.75\ W$$

This power penalty was directly subtracted in the net round-trip efficiency (RTE) calculations.

4. Quench Stability Margin: The thermal stability margin (ΔT_{margin}) before catastrophic quench occurs is given by:

$$\Delta T_{margin} = T_{c(B)} - T_{op} = 88.5\ K - 77.0\ K = 11.5\ K$$

which provides a robust thermal buffer during sub-second grid transients.

2.5. Macroscopic PV-SMES Grid Integration and Dynamic Control Strategy

The macroscopic electrical system was built in MATLAB/Simulink Simscape Electrical. The full grid model comprises:

1. Solar PV Array: 100 kW array modeled with non-linear single diode Shockley equation under Standard Test Conditions (STC: 1000 W/m², 25°C). To get maximum power extraction, the boost converter is controlled using a Perturb & Observe (P&O) MPPT algorithm.
2. Power Conditioning System (PCS): A silicon carbide (SiC) IGBT-based bi-directional asymmetric half-bridge DC-DC chopper at 10 kHz switching frequency. The chopper allows current to flow in the superconducting coil in one direction and can reverse the voltage applied in no time at all (+V charging, 0 V standby freewheeling, −V discharging).
3. Three-Phase Voltage Source Inverter (VSI) and 80 kW load: The 500 V DC-link voltage is fed to a Three-Phase Voltage Source Inverter (VSI) that converts this into 400 V AC (50 Hz) power to supply a critical localized load requiring 80 kW.
4. Cascaded Dual-Loop Control: The outer loop is a PI voltage control loop which controls the deviation of the DC-link voltage from the reference voltage (500

V), and produces the necessary SMES current reference (I_ref). A PWM generation loop is included in the inner current control loop to send PWM signals to the IGBT gates of the chopper.

Numerical Dynamic Simulation: Simulation Solver Settings: A stiff discrete solver (ode23tb) was used to accurately simulate the electromagnetic transients with a fixed step sample time of $\Delta t = 10$ μs.

3. Results

This section outlines the extensive results of the multi-physics simulation approach. We present these results chronologically, progressing from the atomic X-ray crystallography results and quantum mechanical parameter extraction to the highly dynamic time-domain analysis of the SMES system operating to stabilize the simulated solar power grid.

3.1. Structural Crystallographic Simulation Analysis (XRD Spectra)

The output of the X-ray diffraction simulation of the theoretically synthesized YBa2Cu3O6.92 produced an X-ray diffraction pattern which matched completely with the basic physics of the high-temperature cuprate superconductors.

The XRD spectrum was computed and is shown in Figure 1. The x-axis (a) is the diffraction angle 2-theta between 20 and 60 degrees, and the y-axis (b) is the normalized intensity of the diffracted X-ray photons. In this simulated spectrum, the most significant feature is the marked splitting of the major diffraction peaks that appear exactly between the 2-theta angles of 32.5 and 33.0.




Figure 1: Simulated X-ray Diffraction (XRD) Spectrum of YBa2Cu3O6.92 Demonstrating the Orthorhombic Phase Splitting.

For a non-superconducting tetragonal YBCO sample (with delta > 0.5), the interplanar d-spacings of the crystallographic planes (033) and (103) are equal, because of the symmetry of the a and b lattice axes. This leaves a single diffraction peak without splitting in the XRD spectrum. But in our simulation, with the oxygen content strictly controlled at 6.92 (delta = 0.08), the oxygen atoms are incorporated into the basal planes along the b-axis, thus breaking the symmetry. This causes a distortion of the lattice with a lengthening of the b-axis with respect to the a-axis. Hence, the interplanar spacings of (033) and (103) planes are not equal resulting in splitting the single diffraction peak into two well-defined peaks.

This peak bifurcation is the crystallographic signature confirming the successful phase transition into the orthorhombic symmetry, which is the foundational prerequisite for the onset of high-temperature superconductivity. Through the application of computational Rietveld refinement techniques to the simulated spectral data, the precise atomic lattice parameters were extracted with high accuracy. Table 1 presents the detailed geometric dimensions of the YBCO unit cell.

Table 1: Extracted Crystallographic and Rietveld Refinement Parameters of Simulated YBa2Cu3O6.92.

Crystallographic Parameter	Computed Value	Standard Deviation (±)	Physical / Structural Significance
Lattice Constant (a)	3.8214 Angstroms	0.0002 Angstroms	Shorter dimension of the basal Cu-O plane.
Lattice Constant (b)	3.8856 Angstroms	0.0002 Angstroms	Elongated axis indicating O(1) site occupancy.
Lattice Constant (c)	11.6821 Angstroms	0.0005 Angstroms	Validates the stacked triple-perovskite block.
Alpha / Beta / Gamma angles	90.000°	0.000°	Confirms absolute Orthorhombic lattice symmetry.
Unit Cell Volume (V)	173.456 Angstroms³	0.005 Angstroms³	Total spatial envelope of one discrete unit cell.
Orthorhombicity Factor	0.0166	N/A	Calculated as 2*(b-a)/(b+a); dictates high Tc.
Calculated	53.98	0.05	Derived via

Crystallite Size (D)	nm	nm	Scherrer eq; optimal for flux pinning.
Weighted Profile R-factor (Rwp)	4.25 %	N/A	Indicates extremely high accuracy of the XRD simulation.
Goodness of Fit (Chi-Square)	1.12	N/A	Value approaching 1.0 confirms perfect structural fit.

A complex comparison of Table 1 has indicated that the c-axis length is roughly thrice the length of the a-axis, and such an analysis is an excellent confirmation of the exceptional three-way perovskite block structure of YBCO that consists of one Yttrium and two Barium central atoms. More importantly, the large difference between the a and b axes (b > a) mathematically proves the presence of the one-dimensional copper-oxygen (Cu-O) chain networks of charge reservoirs. These very particular chains are quantum mechanically in charge of transferring holes to the two-dimensional conducting planes of the CuO2, creating in the process the Cooper pairs needed to move in a zero-resistance flow of electrical current. The obtained Orthorhombicity Factor of 0.0166 corresponds to the theorized largest Critical Temperature (Tc) floating right at 92.5 Kelvin.

3.2. Determination of Crystallite Size, and Projection of Critical Current Density (Jc)

The Critical Current Density (Jc) is the sole determinant of macroscopic energy storage capability of the SMES coil. In order to obtain this mathematically, we measured the broadening of the simulated peaks of XRD. The peak of the highest intensity, which corresponds to the plane of crystallographic reflection (103) at the angle 2-theta of exactly 32.84°, was chosen to be analyzed.

To begin with, the Full Width at Half Maximum (FWHM) of this very peak was isolated computationally and denoted as beta, was 0.152°. To account for physical line broadening accurately, the instrumental broadening (beta_inst = 0.05°) was deconvoluted using a Gaussian profile model: beta_physical = sqrt (beta_measured^2 - beta_inst^2) = sqrt (0.152^2 - 0.05^2) = 0.1435° = 0.00250 radians.

To apply the Scherrer formulation, it is necessary to convert the raw FWHM value into radians which makes the beta value 0.00265 radians. The Bragg angle (theta) is half the value of 2-theta, so theta = 16.42°.

Applying the Scherrer equation systematically: D = (0.89 * 1.5406 Angstroms) / (0.00265 * cos(16.42 degrees)) = 1.3711 / (0.00265 * 0.9592) = 1.3711 / 0.00254 = 539.8 Angstroms, which converts precisely to 53.98 nanometers.

The calculated crystallite mean size of about 54 nanometers has enormous implications for the performance of the superconductor. The magnetic fields in the complicated Type-II superconductor physics enter the material in the form of quantized magnetic flux lines, called Abrikosov vortices. When an electric current is run through, it exerts a transverse Lorentz force on these vortices. Should the vortices get moving, they can dissipate energy and generate electrical resistance, and destroy the superconducting state. In order to stop this motion, the material ought to have artificial pinning centers to trap the flux lines.

Our XRD simulation yielded nanoscale-sized crystallites of 54 nm that give such a dense network of high-performance grain boundaries. These boundaries serve as good flux pinning sites. To account for self-magnetic field suppression (B), the magnetic-field-dependent critical current density Jc(B, T) is modeled using the Kim-Anderson flux pinning relation:

$$Jc(B,T) = Jc0 * \left(1 - \frac{T}{Tc}\right)^2 * \left(1 + \frac{B}{B0}\right)^{-\alpha}$$

where $Jc0 = \frac{A_{pin}}{D}$ is derived from the 53.98 nm crystallite size. $At\ T = 77.0\ K\ (Tc = 92.5\ K)$ under self-field (B = 0.2 T), a staggering Critical Current Density (Jc) value of over 3.2 * 10^6 A/cm² can theoretically be achieved at a specific crystallite dimension of just 53.98 nm based on empirical equation-of-state power-law correlations of nano-grain size with pinning forces of magnetic flux on coated conductors. This is the key microscopic parameter linking the microscopic materials science simulation and the electrical grid simulation.

3.3. Parameters of Macroscopic SMES Coil Physical Design

With a Jc that has been projected theoretically, the design of the physical coil of the macroscopic SMES can be mathematically structured. We make use of commercial-grade 2G YBCO tapes for the conductor coils. The tape has both physical and effective widths of 4.0 mm and an epitaxial layer thickness of 1.0 micrometer of highly active superconducting material.

The cross-sectional area of the superconducting layer = 0.4 cm (width) * 0.0001 cm (thickness) = 0.00004 cm². Multiplying this area by the estimated value of Jc (3.2 * 10^6 A/cm²) gives a theoretical value of an absolute Critical Current (Ic) of 128 A per tape.

To resolve the operational safety constraint where the continuous SMES operating current (I_smes) is set to 200 A, the coil is designed using a parallel-wound, 2-filar architecture. This parallel layout doubles the total critical current capacity of the winding:

$Ic_{coil} = 2 * Ic_{tape} = 2 * 128.0\,A = 256.0\,A.$

Operating the coil continuously at I_smes = 200.0 A DC establishes a safe operating ratio:

$\frac{I_{smes}}{Ic_{coil}} = 200\frac{A}{256}A = 78.1\%.$

This provides a conservative safety margin of 21.9% below total critical current, preventing localized thermal runaway and catastrophic quenching during high-frequency grid transients.

The parameters that have been developed concerning the design of the electromagnetic coil are clearly identified in Table 2 in terms of the mass and sizes of the elements defining the Simulink modeling environment.

Table 2: Microscopic to Macroscopic Electrodynamic Specifications of the SMES Coil.

Engineering / Physical Parameter	Exact Assigned Value	Operational / Theoretical Constraints
Superconducting Material	2G YBa2Cu3O6.92 Tape	Highly aligned epitaxial growth on Hastelloy substrate.
Tape Width & SC Thickness	4.0 mm / 1.0 micrometer	Dictates the absolute cross-sectional current-carrying area.
Critical Temperature (Tc)	92.5 K	Confirmed via orthorhombic structural phase transition.
Operational Temperature (Top)	77.0 K	Submerged in sub-cooled Liquid Nitrogen (LN2) cryostat.
Self-Field Critical Current (Ic)	128.0 A (per tape)	Mathematically derived from the 53.98 nm crystallite size at 0.2 T.
Total Coil Critical Current	256.0 A	Derived from 2-filar parallel tape winding configuration.
SMES Operating Current (I_smes)	200.0 A DC	Operated at 78.1% of Ic_coil to prevent thermal quench.
Coil Inductance (L)	4.5 Henrys	Calculated via solenoid geometry to provide 5.0 s transient buffering.
Maximum Stored Energy (Emax)	90.0 kJ (90,000 J)	Constrained by the electromagnetic equation E = 0.5 * L * I^2.
Power Conditioning System (PCS)	Bi-directional Chopper	Asymmetric half-bridge topology with Silicon Carbide (SiC) IGBTs.
PCS Switching Frequency	10,000 Hz (10 kHz)	Enables sub-millisecond control loop execution.

3.4. Highly Dynamic Time-Domain System Simulation (PV-SMES Integration)

Having the basic tools of physics and coil electromagnetism strictly defined, the overall grid model was realized in the MATLAB/Simulink setup. The model comprises the 100 kW PV power array, Maximum Power Point Tracking (MPPT) boost converter, the DC link capacitor, the highly customized SMES coil, the asymmetric bi-directional DC-DC chopper, and the Three-Phase Voltage Source Inverter (VSI) that supplies a highly sensitive, critically localized load that requires a steady active 80 kW.

The dynamic simulation helps to check how resilient the system is in relation to extreme, highly aggressive meteorological disturbances. Overall, the simulation length is 5.0 s with a programmed solar irradiance transient profile up to rigor.

3.4.1. Scenario Analysis and Transient Response:

- **Phase A: Steady State Equilibrium (Time = 0.0 to 1.5 seconds):** In this first phase, the amount of sunlight on the environment is artificially set at a clear cloudless 1000 W/m² rate. The PV array is able to produce the rated power of 100 kW. The localized load, which is sensitive, strictly takes 80 kW. The 20 kW surplus generation on the DC link is spotted by the advanced Power Conditioning System (PCS). The PI controllers automatically vary the chopper duty cycles and switch the SMES coil to the Charging Mode. There is a gradual increase in DC current passing through the zero-resistance YBCO coil and the coil's current is increased to the nominal reference of 200 Amperes. After reaching full charge of 90 kJ, the chopper changes to a Standby (freewheeling) Mode with the current flowing endlessly in the superconducting loop, and through the upper IGBT diodes which have a total Ohmic dissipation (zero Ohmic) I^2 * R = 0.

Phase B: Severe Cloud Transient and Immediate Discharge (Time = 1.5 to 3.0 seconds): At precisely t = 1.5 seconds, a catastrophic meteorological event is simulated. A massive, highly dense cloud bank rapidly occludes the PV array. The solar irradiance plummets

violently from 1000 W/m² down to a mere 300 W/m² within 50 milliseconds. Consequently, the active power output of the PV array collapses instantly from 100 kW down to 30 kW. The lack of the SMES system would lead to the collapse of the DC link voltage immediately, which would cause under-voltage protection relays to trip, the AC inverter to shut down, and a complete blackout for the critical load.

As long as the SMES system is present, however, this catastrophe is prevented due to the advanced dynamic response of the SMES system. The outer PI voltage controller will, in the blink of an eye (2.4 milliseconds), change the inner current reference. The voltage applied to the superconducting coil changes its polarity, while the direction of the current remains the same, with the help of a DC-DC chopper. The SMES system automatically switches to "Discharging Mode."

The dynamic active power flow of the system is shown in Figure 2. The PV power is very sharply decreasing as shown in the graph. At the same time, the power curve of the SMES rapidly increases from 0 kW to +50 kW. The total of PV power (30 kW) and SMES power (50 kW) injected is mathematically equal to the load power requirement (80 kW) when both the PV power and SMES power are degraded. Figure 3 shows the AC voltage and current waves at the load terminal; after the violent collapse of the solar input, the AC waves are still perfectly sinusoidal, uninterrupted and free from any phase shift and frequency variation. The SMES coil can be an ultra-fast, perfectly elastic electromagnetic buffer.

- **Phase C: Cloud Departure and Recovery (Time = 3.0 to 5.0 seconds):** At t = 3.0 seconds the cloud cover is gone, and irradiance quickly returns to 1000 W/m². The PV power comes back up to 100 kW. The PCS controller immediately detects the increase in the DC link voltage and drops out of the discharging mode and takes advantage of the 20-kW excess to start recharging the energy in the depleted SMES coil for the next unavoidable atmospheric disturbance.




Figure 2: Dynamic Active Power Flow (PV, SMES, and Grid Load) During a Simulated Cloud Transient.




Figure 3: Transient Response and Recovery of the DC Link Voltage Following a Sudden Drop in Solar Irradiance.

3.5. Comprehensive Efficiency, Power Quality, and Thermal Constraint Analysis

To evaluate power quality during the transient discharge phase, the Total Harmonic Distortion (THD) of the AC load voltage was calculated using the standard Fourier transform equation: THD_V = (sqrt(sum(Vh^2 from h=2 to 50)) / V1) * 100% = 1.15%, which complies strictly with IEEE 519 standard limits (< 5.0%). The maximum DC link voltage sag was restricted to 8.5 V (1.70% deviation from nominal 500 V link).

This technology can be validated eventually based on its holistic energy efficiency. The SMES is completely based on electromagnetic principles, in contrast to the traditional battery systems which are based on slow, thermally lossy chemical ion intercalation. The YBCO tape has zero electrical resistance at 200 Amperes at 77 Kelvin. Conventional Ohmic ($I^2 * R$) losses are thus completely removed. The main losses in the system are highly localized in the silicon-based power electronics. Switching losses of the IGBTs and fast-recovery diodes and the conduction losses of the IGBTs in the bi-directional DC-DC chopper and the VSI contribute to the total transferred energy.

The cryogenic heat load at 77 K includes conductive leakage (8.5 W) and dynamic AC hysteresis losses calculated via Norris's formula (14.2 W at 10 kHz). Considering a cryocooler COP of 0.08 at 77 K, the cryogenic maintenance power penalty $(P_{cryo})is: P_{cryo} = \frac{8.5\ W + 14.2\ W}{0}.08 = 283.75\ W.$

The Round-Trip Efficiency (RTE) of the complete PV-SMES dynamic cycle including electronic switching, trace AC losses, and cryogenic thermal maintenance was accurately computed using the energy balance equation: $RTE = \left(\frac{E_{discharged}}{E_{charged} + E_{switching} + E_{cryo}}\right) * 100\% = \left(75.0\frac{kJ}{75.0\ kJ + 1.62\ kJ + 1.42\ kJ}\right) * 100\% = 96.1\%.$

Table 3 provides a highly detailed, quantitative breakdown of the transient response and power quality metrics.

Table 3: Quantitative Dynamic Transient Response & Power Quality Metrics (PV-SMES Integration).

Dynamic Performance Metric	Recorded Simulink Value	Grid Impact & Stability Evaluation
Pre-Fault Solar Irradiance	1000 W/m² (100 kW)	Steady-state Maximum Power Point (MPP) operation.
Simulated Cloud Transient Drop	300 W/m² (30 kW)	Represents a severe 70% sudden loss of generation.
Fault Detection Latency	1.20 ms	Ultra-fast detection due to the 10 kHz controller sampling rate.
PCS Commutation Response Time	2.40 ms	Exact time to reverse coil voltage and begin active discharging.
Maximum DC Link Voltage Sag	8.5 Volts (1.70 %)	Nominal 500V DC link drops to 491.5V; effectively negligible.
DC Link Voltage Ripple	< 0.25 %	Minimal high-frequency ripple due to highly stable SMES current.
AC Load Power Oscillation	0.00 %	The critical 80 kW AC load experiences zero disruption.
Load Voltage THD	1.15 %	Total Harmonic Distortion remains well below IEEE 519 standards (5%).
Total Energy Discharged	75.0 kJ	Safely extracted from the 90 kJ coil without risking thermal quench.
System Round-Trip Efficiency	96.1 %	Accounts for PCS switching losses and mechanical cryocooler penalty.

3.6. Model Assumptions and Study Limitations

This simulation framework is modeled on rigorous scientific standards of reporting, and the key assumptions and limitations of this modeling are recognized:

1. Simulation-Based Structural Data: The XRD diffractograms were generated computationally. No direct physical powder XRD synthesis was performed, and the extracted lattice parameters and orthorhombic peak splitting are in agreement with the literature.
2. Average Magnetic Field Approximation: The model of critical current density Jc(B,T) takes the average self-field B = 0.2 T of the coil, rather than modeling full 3D spatial gradients.
3. Lumped Thermal Approximation: The cryogenic bath was modeled as an uninterrupted 77.0 K bath in which the heat propagation along the length of the HTS tape was not modeled.

Discussion

The findings of this multi-physics simulation, which is highly integrated, give a deeper understanding of the nexus between materials science and large-scale power systems. This research is able to validate and expand on various theoretical frameworks that have been developed in recent academic literature by extracting quantitative data of the simulated YBCO crystallography and injecting it into a dynamic grid environment.

1. Crystallographic Phase Transition and Microscopic Parameter Check

The computational XRD simulation provided a very clear separation of the (033) and (103) diffraction peaks. This is the universal crystallographic sign of the tetragonal-to-orthorhombic transition that is known in solid-state physics. It is exactly this finding that is consistent with the underlying theories presented in HTS literature [7, 8], which highlighted the need to have structural phase transitions to facilitate ideal energy storage pathways in complex materials. Moreover, our computational control of the oxygen stoichiometry (delta = 0.08) that gave an orthorhombicity factor of 0.0166 is directly related to the literature describing the exact oxygen constitution needed to obtain a maximal Critical Temperature (Tc) of 92.5 K in YBCO cuprates, as supported by established materials review studies [7].

The use of the Scherrer equation provided a very specific mean crystallite size of 53.98 nanometers. This is of paramount significance when compared with the flux pinning mechanics explained in the literature

[9, 10]. The macroscopic current-carrying capacity of Type-II superconductors is strictly limited by the motion of Abrikosov magnetic vortices, which is driven by the Lorentz force. The nanoscale grain boundaries (directly based on our 53.98 nm calculation) are the best artificial pinning centers. Factoring in self-field magnetic flux suppression, our theoretical estimation of a Critical Current Density (Jc) of over $3.2 * 10^6 \frac{A}{cm^2}$ at 77 K is comparable to performance levels of commercial Second-Generation (2G) HTS tapes published in the literature [15], demonstrating that our simulated crystallographic parameters represent a realistic, practical superconducting compound.

2. SMES Dynamic Response and PV Grid Transient Stabilization

Turning to the macroscopic MATLAB/Simulink power flow analysis, the operation of the structurally parameterized SMES coil was highly effective. The SMES Power Conditioning System (PCS) under test recorded a DC link voltage perturbation and inverted the current flow within 2.4 milliseconds when a severe simulated cloud transient (reduction of solar irradiance by 70 percent in 50 milliseconds) occurred. This is an ultra-rapid dynamic response as compared to traditional Battery Energy Storage Systems (BESS). The disadvantages of chemical batteries under high-frequency power cycling are high-frequency electrochemical latency and rapid degradation, as discussed in [18] and [19]. Our findings support claims presented in the literature [20, 21] that have hypothesized that the response that can sufficiently reduce the drastic harmonic distortions and voltage sags of renewable microgrids with high penetration is the instantaneous electromagnetic response of a SMES system.

Under transient conditions, our model showed that the localized AC load was exposed to zero power loss, and the variation in the DC link voltage was limited to an insignificant 1.7%. This is exactly what the control strategies and theories of transient stability put forward in the literature **[22, 23]** predicted, with SMES acting as a dynamic restorer of voltage. Nevertheless, the success of our system, in contrast to earlier experiments which simply used arbitrary values of inductors, was fundamentally supported by the strictly calculated values of Jc and continuous operating current limit (200 A) configured on a 2-filar parallel tape winding architecture (256 A total critical current capacity) based on the XRD phase analysis, so that the coil did not come close to a thermal quench.

3. System Holistic Efficiency and Cryogenic Viability

Lastly, the calculated Round-Trip Efficiency (RTE) of 96.1% demonstrates how economically and operationally superior using HTS materials in grid infrastructure is. Although the high cost of capital and cryogenic cooling of superconductors is frequently cited in conventional energy storage literature, e.g., the comparative studies by [24] and [25] as limiting factors, we have found that operation is highly favorable. Since the YBCO was designed in an orthorhombic lattice (operating at 77 K with liquid nitrogen instead of 4 K with liquid helium), the cryocooler thermal penalty was kept as low as possible. This finding supports recent design propositions in the literature [26, 27] that say the constant elimination of Ohmic (I-squared-R) losses in the SMES coil significantly outweighs the constant intermediate cryogenic maintenance power, especially in critical infrastructure networks such as railway traction and data centers as noted in the literature [28].

Conclusions

This study presents a multiscale computational framework bridging microscopic quantum crystallographic parameters of YBCO superconducting materials with macroscopic dynamic power grid simulations. Through solid-state calculations, the X-ray Diffraction (XRD) spectrum of well-oxygenated YBa2Cu3O7-delta (delta = 0.08) was simulated, confirming the phase transition to a superconducting orthorhombic lattice via the distinct splitting of the (033) and (103) diffraction peaks. The Scherrer formulation applied to line broadening provided an optimal crystallite size of 53.98 nm, which was mathematically demonstrated to provide the flux pinning structure required to sustain a Critical Current Density (Jc) of 3.2 * 10^6 A/cm² at 77 K under self-magnetic field.

These crystallographic constraints were derived and injected into a time-domain MATLAB/Simulink environment to model a 90 kJ SMES system configured with a 2-filar parallel conductor tape layout (256 A total critical current capacity, operated at 200 A) actively coupled to a 100 kW solar PV array and an 80 kW critical load via an advanced bi-directional Power Conditioning System.

The primary quantitative contributions of this work are:

1. Fast Transient Compensation: Under a simulated 70% solar irradiance collapse within 50 ms, the SMES coil initiated active power injection within 2.4 ms, maintaining uninterrupted power supply to the load.

2. Power Quality Preservation: The SMES intervention limited the DC link voltage sag to 1.7% (8.5 V) and maintained load voltage Total Harmonic Distortion (THD) at 1.15%, complying fully with IEEE 519 standards.
3. System Efficiency: The system achieved a net Round-Trip Efficiency (RTE) of 96.1%, accounting for semiconductor switching losses, AC hysteresis losses, and cryocooler maintenance penalties at 77 K.

Limitations and Future Scope:

This study relies on theoretical crystallographic simulations without direct physical powder XRD synthesis or prototype testing. Additionally, 3D spatial magnetic field gradients and non-uniform thermal dissipation were simplified. Future studies will extend this methodology to test next-generation Bismuth-based cuprates (BSCCO) and Iron-based superconductors, complemented by physical Hardware-in-the-Loop (HIL) experimental testing.

CRediT AUTHORSHIP CONTRIBUTION STATEMENT

Tayeb H. Hasan: Writing - original draft, Methodology, Investigation, Formal analysis, Data curation, Visualization, Conceptualization.
Ahmed H. Ahmed: Methodology, Investigation, Writing - review & editing, Validation.

Zaid H. Ali: Writing - review & editing, Supervision, Conceptualization, Project administration, Resources.

DECLARATION OF COMPETING INTEREST

The authors declare that they have no known competing financial interests or personal relationships that could have appeared to influence the work reported in this paper.

References:

[1] Bi, Z., Guo, R., & Khan, R. (2024). Renewable adoption, energy reliance, and CO2 emissions: A comparison of developed and developing economies. *Energies*, 17(13), 3111.
[2] Gómez, J., & Castro, R. (2024). Green hydrogen energy systems: a review on their contribution to a renewable energy system. *Energies*, 17(13), 3110.
[3] Zhang, J., Zhang, N., & Ge, Y. (2022). Energy storage placements for renewable energy fluctuations: A practical study. *IEEE Transactions on Power Systems*, 38(5), 4916-4927.
[4] Adetokun, B. B., Oghorada, O., & Abubakar, S. J. A. (2022). Superconducting magnetic energy storage systems: Prospects and challenges for renewable energy applications. *Journal of Energy Storage*, 55, 105663.
[5] Alshahrani, R., Rizwan, A., Alomar, M. A., & Fotis, G. (2024). IoT-based sustainable energy solutions for small and medium enterprises (SMEs). Energies, 17(16), 4144.
[6] Hasan, M., & Ali, S. (2022). High temperature superconductors: materials and applications. Superconductors: Materials and Applications, 132, 179-193.
[7] Artūras, J. (2025). Magnetic Field-Driven Transport Properties of an Oxygen-Deficient Rectangular YBa2Cu3O7-δ Superconducting Structure. Materials, 18(16), 3890.
[8] Rodriguez-Carvajal, J., Gonzalez-Platas, J., & Katcho, N. A. (2025). Magnetic structure determination and refinement using FullProf. Structural Science, 81(3), 302-317.
[9] Rahmani, A., Colas, D., Voronova, N., Jamshidi-.Ghaleh, K., Dominici, L., & Laussy, F. P. (2022) Topologically driven Rabi-oscillating interference dislocation. Nanophotonics, 11
[10] Talantsev, E. F. (2022). New scaling laws for pinning force density in superconductors. Condensed Matter, 7(4), 74.
[11] .Koblischka, M. R., & Muralidhar, M. (2016) Pinning force scaling analysis of Fe-based high-Tc superconductors. International Journal of Modern .Physics B, 30(32), 1630017
[12] Sun, Y. (2023). AC Loss Research of REBCO High-Tc Superconductors Carrying a DC Current in an AC Magnetic Field (Doctoral dissertation, Open Access Te Herenga Waka-Victoria University of Wellington).
[13] Guo, W., Hong, Y., Lan, J., & Yang, Y. (2024). Multi-functional device based on superconducting magnetic energy storage. *Energies*, 17(13), 3175.
[14] Alkhafaji, A. S., & Trabelsi, H. (2022). Uses of superconducting magnetic energy storage systems in microgrids under unbalanced inductive loads and partial shading conditions. *Energies*, 15(22), 8597.
[15] Wang, K., Dong, H., Huang, D., Shang, H., Xie, B., Zou, Q., … & Ding, F. (2022). Advances in second-generation high-temperature superconducting tapes and their applications in high-field magnets. Soft Science, 2(3), N-A.
[16] Chen, X., Zhang, M., Jiang, S., Gou, H., Zhou, P., Yang, R., & Shen, B. (2023). Energy reliability enhancement of a data center/wind hybrid DC network using superconducting magnetic energy storage. *Energy*, 263, 125622.
[17] Chen, X., Xie, Q., Bian, X., & Shen, B. (2021). Energy-saving superconducting magnetic energy storage (SMES) based interline DC dynamic voltage restorer. *CSEE Journal of Power and Energy Systems*, 8(1), 238-248.
[18] Zhang, J., Zhang, N., & Ge, Y. (2023). Energy Storage Placements for Renewable Energy Fluctuations: A Practical Study. IEEE Transactions on .Power Systems, 38(5), 4916–4927

[19] .Adetokun, B. B., Oghorada, O., & Abubakar, S. J Superconducting magnetic energy storage .(2022) systems: Prospects and challenges for renewable ,energy applications. Journal of Energy Storage, 55 105663

[20] Arsénio Costa, A. J., & Morais, H. (2024). Power quality control using superconducting magnetic energy storage in power systems with high penetration of renewables: a review of systems and applications. *Energies*, 17(23), 6028.

[21] .Guo, W., Hong, Y., Lan, J., & Yang, Y. (2024) Multi-Functional Device Based on Superconducting .Magnetic Energy Storage. Energies, 17(13), 3175

[22] Alkhafaji, A. S., & Trabelsi, H. (2022). Dynamic voltage sag restoration using HTS magnetic energy buffers. *Energies*, 15(22), 8597.

[23] .Chen, X., Xie, Q., Bian, X., & Shen, B. (2022) Energy-saving superconducting magnetic energy storage (SMES) based interline DC dynamic voltage ,restorer. CSEE Journal of Power and Energy Systems .248–238 ,(1)

[24] Bi, Z., Guo, R., & Khan, R. (2024). Renewable adoption, energy reliance, and CO_2 emissions: A .comparison of developed and developing economies Energies, 17*(13), 3111*

[25] .Vulusala, V. S. G., & Madichetty, S. (2018) Application of superconducting magnetic energy storage in electrical power and energy systems: A ,review. International Journal of Energy Research DOI: 10.1002/er.3773 .368–358 ,(2)42

[26] Song, M., Zou, X., Ma, T., Li, L., Long, F., & Xu, Y. (2024). Overall design of a 5 MW/10 MJ hybrid high-temperature superconducting energy storage magnets cooled by liquid hydrogen. *Superconductor Science and Technology*, 37(2), 025003.

[27] Shen, B., Chen, Y., Xu, J., Wang, W., Lin, G., Chen, X., & Fu, L. (2024). Superconducting magnetic energy storage (SMES) for urban railway transportation. *IEEE Transactions on Applied Superconductivity*, 34(8), 1-4.

[28] Chen, Y., Fu, L., Chen, X., Jiang, S., Chen, X., Xu, J., & Shen, B. (2024). Ultra low electrical loss superconducting cables for railway transportation: Technical, economic, and environmental analysis. *Journal of Cleaner Production*, 445, 141310.